

[Time: 3 Hours]

[Marks:80]

Please check whether you have got the right question paper.

- N.B:**
1. **Question No.1 is compulsory.**
 2. **Attempt any three questions out of remaining five.**
 3. Assume suitable data if required.

Q.1 Answer the following

20

a) Determine whether the following signals are energy signals or power signals and calculate their energy or power.

(1) $x(t) = e^{-2t} u(t)$

(2) $x[n] = \left(\frac{1}{2}\right)^n u[n]$

b) Determine if following system is memoryless, casual, linear, time invariant.

$y(t) = 10x(t) + 5$

c) Determine Fourier transform of $x(t)$ using time shifting property

$x(t) = e^{-3|t-t_0|} + e^{3|t+t_0|}$

d) Find out even and odd components of the following signals:


(i) $x[n] = u[n] - u[n-5]$

(ii) $x(t) = 3+2t+5t^2$

e) Determine relation between continuous time Fourier Transform and Laplace Transform.

Q.2 a) Determine Fourier Series representation of the following signal:

10



Q.2 b) Find impulse response of continuous time systems governed by following transfer function.

10

(i) $H(s) = \frac{1}{s^2(s-2)}$

(ii) $H(s) = \frac{1}{s(s+1)(s-2)}$

Q.3 a) A continuous time signals is defined as,

10

$x(t) = t; \quad 0 \leq t \leq 3$

$x(t) = 0; \quad t > 3$

Q.P. Code :11967

Sketch waveforms of following signals:

- (i) $x(-t)$ (ii) $x(2-t)$ (iii) $x(3t)$ (iv) $x(0.5t+1)$


Q.3 b) Determine inverse z-transform of the following function: 05
 $X[Z] = \log(1+az^{-1}); |z| > |a|$

Q.3 c) Compute DTFT of sequence $x[n] = \{0, 1, 2, 3\}$. Also Sketch magnitude and phase spectrum. 05

Q.4 a) Using Laplace Transform determine complete response of system described by following equation. 10
 $\frac{d^2y(t)}{dt^2} + 5\frac{dy(t)}{dt} + 4y(t) = \frac{dx(t)}{dt}$ where $y(0) = 0; \frac{dy(t)}{dt} \Big|_{t=0} = 1$, for input $x(t) = e^{-2t}u(t)$

Q.4 b) Find impulse response of system described by following difference equation 10
 $y[n] - 3y[n-1] - 4y[n-2] = x[n] + 2x[n-1]$ where all initial conditions are zero.

Q.5 a) For the following continuous time signals, determine Fourier Transform. 10
 (i) $x(t) = e^{-at} \sin \omega_0 t u(t)$



Q.5 b) Determine Fourier series representation of $x[n] = 4\cos\left[\frac{\pi n}{2}\right]$ 05

Q.5 c) Determine cross correlation of sequence $x[n] = \{1, 1, 2, 2\}$ and $y[n] = \{1, 3, 1\}$ 05

Q.6 a) The input signal $x(t)$ and impulse response $h(t)$ of a continuous-time system are described as follows 10
 $x(t) = e^{-3t}u(t)$ and $h(t) = u(t-1)$. Find output of system using convolution integral.

b) Determine Z Transform and ROC of 05
 (i) $x[n] = a^n u[n-1]$ 05
 (ii) $x[n] = a^n \cos \omega_0 n u[n]$ 05
